

Mode 1 channel	Mode 2 channel	8 bit channel	Value	Function	Type of control
			120-127	White	step
			128-255	Enable macro color function on channel 7	step
9	9	7	0	3-facet prism rotatin control,Prism macros Open position (no prism)	step
			1- 63	Forwards rotation from fast to slow	proportional
			64	No rotation	step
			65-127	Backwards rotation from slow to fast	proportional
			128-255	Prism/gobo macros	
			128-135	Macro 1	step
			136-143	Macro 2	step
			144-151	Macro 3	step
			152-159	Macro 4	step
			160-167	Macro 5	step
			168-175	Macro 6	step
			176-183	Macro 7	step
			184-191	Macro 8	step
			192-199	Macro 9	step
			200-207	Macro 10	step
			208-215	Macro 11	step
			216-223	Macro 12	step
			224-231	Macro 13	step
			232-239	Macro 14	step
			240-247	Macro 15	step
			248-255	Macro 16	step
10	10	8	0-7	Static gobos Open/hole	step
			8-15	Gobo 1	step
			16-23	Gobo 2	step
			24-31	Gobo 3	step
			32-39	Gobo 4	step
			40-47	Gobo 5	step
			48-55	Gobo 6	step
			56-63	Gobo 7	step
			64-71	Gobo 8	step
			72-79	Gobo 9	step
			80-223	Shaking gobos with variable speed	
			80-95	Gobo 1	step
			96-111	Gobo 2	step
			112-127	Gobo 3	step
			128-143	Gobo 4	step
			144-159	Gobo 5	step
			160-175	Gobo 6	step
			176-191	Gobo 7	step
			192-207	Gobo 8	step
			208-223	Gobo 9	step
			224-255	Gobo wheel rotation from slow to fast	proportional
11	11	9	0-31	Rotating gobos Open/hole	step
			32-63	Rot.gobo 1 (metal)	step
			64-95	Rot.gobo 2 (metal)	step
			96-127	Rot.gobo 3 (metal)	step
			128-159	Rot.gobo 4 (dichroic)	step
			160-191	Rot.gobo 5 (dichroic)	step
			192-223	Rot.gobo 6 (glass)	step
			224-255	Rot.gobo wheel cont.rotation from slow to fast	proportional

Mode 1 channel	Mode 2 channel	8 bit channel	Value	Function	Type of control
12	12	10	0-127 128-190 191-192 193-255	Rotating gobo index,rotating gobo rotation Gobo indexing Forwards gobo rotation from fast to slow No rotation Backwards gobo rotation from slow to fast	proportional proportional step proportional
13	13	11	0 1-179 180-191 192-223 224-255	Iris Open Max.diameter to min.diameter Closed Pulse closing from slow to fast Pulse opening from fast to slow	step proportional step proportional proportional
14	14	12	0-85 86-170 171-225	Focus,multistep zoom Zoom 15°-Continuous adjustment from far to near Zoom 18°-Continuous adjustment from far to near Zoom 22°-Continuous adjustment from far to near	proportional proportional proportional
15	15	13	0-31 32-63 64-95 96-127 128-159 160-191 192-223 224-255	Shutter,stroke Shutter closed No function (Shutter open) Strobe-effect from slow to fast (max.10 flashes/s) No function (Shutter open) Pulse-effect in sequences from slow to fast No function (Shutter open) Random strobe-effect from slow to fast No function (Shutter open)	step step proportional step proportional step proportional step
16	16	14	0-255	Dimmer intensity Gradual adjustment of the dimmer intensity from 0 to 100%	proportional