

# DMX Control 1024™

Thanks to two DMX 512 outputs, it is possible with this fixture to control up to 1024 DMX channels - or 48 lighting fixtures of up to 32 channels each. The DMX Control 1024 supports Robe and all other popular lighting brands. A show can be created from up to 4752 scenes, consisting of presets and chases. The range of 1152 shows, presets and/or chases can be recorded into 24 pages. Flash memory is used, which allows software updates via a compact flash card. The DMX Control 1024 is suitable for all range of AT, CT and LT series.



# Technical Specification

## ELECTRICAL SPECIFICATION

- Power supply: 120/220 V via external Power Supply 9-12 V DC

## MECHANICAL SPECIFICATION

- Height: 102 mm (40.2")
- Width: 483 mm (19.0")
- Length: 267 mm (10.5")
- Weight: 4.5 kg (9.9 lbs)

## CONTROL AND PROGRAMMING

- Real time control of Moving heads and Scanners
- Total 1024 DMX Channels, 2 Universe Outputs
- Control 48 Projectors up to 32 channels each
- 48 fixture groups
- 4752 Programmable Scenes
- 1152 Programmable Presets
- 1152 Programmable Chases
- 1152 Programmable Shows
- Effects Engine
- Large Fixture Library
- Factory ready Color, Gobo, Focus and Effects Presets
- Easily Name Scenes, Chases or Shows using Standard Computer KEY BOARD
- MIDI Function
- 4 Large Rotary Wheels for Menu and Control
- 48 Multi function buttons
- 8 Faders x 4 Banks
- Joystick for PAN and TILT operation
- Desk Lamp socket - XLR connector
- 2x (3pin) + 2x (5pin) DMX Outputs
- 2x polarity switch per output
- Midi-In port, Midi-Out port
- Compact flash card drive
- PS/2 KEY BOARD input
- RCA Audio input

## RIGGING

- Rack size: 19" 4U rack mountable, 6 spaces

