

dmx channel	function	type of control	effect	decimal	percentage
1	X axis, base movement (pan) coarse	proportional	proportional coarse control of the base motor movement	0 - 255	0% - 100%
2	X axis, base movement (pan) fine	proportional	proportional fine control of the base motor movement	0 - 255	0% - 100%
3	Y axis, yoke movement (tilt) coarse	proportional	proportional coarse control of the yoke motor movement	0 - 255	0% - 100%
4	Y axis, yoke movement (tilt) fine	proportional	proportional fine control of the yoke motor movement	0 - 255	0% - 100%
5	movement speed	step	standard (fast)	0 - 10	0% - 4%
		step	ultra fast movement (best for programming positions)	11 - 25	4% - 10%
		proportional	vector mode (from fast to slow)	26 - 127	10% - 50%
		proportional	tracking mode (from fast to slow)	128 - 247	50% - 97%
		step	tracking mode (slow)	248 - 255	97% - 100%
6	dimmer	proportional	gradual adjustment of luminous intensity from 0 to 100%	0 - 255	0% - 100%
7	shutter, strobe and zap effect	step	shutter closed (zap off)	0 - 9	0% - 4%
		proportional	strobe effect with variable speed from slow to fast	10 - 66	4% - 26%
		step	shutter open (zap off)	67 - 68	26% - 27%
		proportional	sequenced pulse effect, slow closing, fast opening (with variable speed from slow to fast)	69 - 125	27% - 49%
		step	shutter open (zap off)	126 - 127	49% - 50%
		proportional	sequenced pulse effect, fast closing, slow opening (with variable speed from fast to slow)	128 - 184	50% - 72%
		step	shutter open (zap off)	185 - 187	73% - 73%
		proportional	random strobe effect, non-synchronised, variable speed from slow to fast	188 - 244	74% - 96%
step	shutter open (zap off)	245 - 255	96% - 100%		
8	zoom effect	proportional	proportional control of zoom effect wheel from narrow to wide beam (from 6° to 13°)	0 - 255	0% - 100%
9	zoom	proportional	proportional control of zoom from narrow to wide beam (from 6° to 80°)	0 - 255	0% - 100%
10	zoom shake	step	no effect	0 - 9	0% - 4%
		proportional	zoom shake effect with variable speed from slow to fast	10 - 71	4% - 28%
		proportional	zoom shake sequenced pulse effect, slow closing, fast opening (with variable speed from slow to fast)	72 - 133	28% - 52%
		proportional	zoom shake sequenced pulse effect, fast closing, slow opening (with variable speed from fast to slow)	134 - 195	53% - 76%
		proportional	zoom shake random strobe effect, non-synchronised, variable speed from slow to fast	196 - 255	77% - 100%
11	selecting effects wheel + shake movement	step	no effect	0 - 9	0% - 4%
			effect 1	10 - 39	4% - 15%
			effect 2	40 - 69	16% - 27%
			effect 3	70 - 99	27% - 39%
			effect 4	100 - 128	39% - 50%
		proportional	shake effect 4 (variable adjustment of oscillation angle from minimum to maximum)	129 - 160	51% - 63%
			shake effect 3 (variable adjustment of oscillation angle from minimum to maximum)	161 - 192	63% - 75%
			shake effect 2 (variable adjustment of oscillation angle from minimum to maximum)	193 - 224	76% - 88%
			shake effect 1 (variable adjustment of oscillation angle from minimum to maximum)	225 - 255	88% - 100%
12	indexing effect rotation through 360°	step	no effect	0 - 9	0% - 4%
		proportional	proportional indexing of the effect through 360°	10 - 128	4% - 50%
		proportional	continuous rotation of the effect in a counter-clockwise direction with proportional control over decreasing speed	129 - 188	51% - 74%
		step	stop effect rotation	189 - 193	74% - 76%
		proportional	continuous rotation of the effect in a clockwise direction with proportional control over increasing speed	194 - 255	76% - 100%

dmx channel	function	type of control	effect	decimal		percentage	
13	selecting colors from the color wheel	step	no colour, white beam	0	- 5	0%	- 2%
			color 1	6	- 14	2%	- 5%
			color 2	15	- 22	6%	- 9%
			color 3	23	- 30	9%	- 12%
			color 4	31	- 38	12%	- 15%
		proportional	from color 5 to colour 1, proportional positioning	46	- 127	18%	- 50%
			rainbow effect from fast to slow in an anticlockwise direction	128	- 190	50%	- 75%
rainbow effect from slow to fast in a clockwise direction	191		- 255	75%	- 100%		
14	cyan	proportional	proportional control of the percentage of cyan color in the light beam from 0 to 100%	0	- 255	0%	- 100%
15	cyan color saturation	proportional	saturation adjustment of cyan color tonality; from bright to dark	0	- 255	0%	- 100%
16	magenta	proportional	proportional control of the percentage of magenta color in the light beam from 0 to 100%	0	- 255	0%	- 100%
17	magenta color saturation	proportional	saturation adjustment of magenta color tonality; from bright to dark	0	- 255	0%	- 100%
18	yellow	proportional	proportional control of the percentage of yellow color in the light beam from 0 to 100%	0	- 255	0%	- 100%
19	CTO	proportional	proportional control of the percentage of CTO in the light beam from 6300°K to 3200°K	0	- 255	0%	- 100%
20	zap effect (effect varies depending upon channel 7 strobe)	step	no effect	0	- 10	0%	- 4%
			zap effect synchronised with the strobe effect, speed and mode selected by strobe channel 7	11	- 30	4%	- 12%
			zap effect, flicker and speed adjustable, speed and mode selected by strobe channel 7	31	- 249	12%	- 98%
			black-out of the light beam during PAN/TILT movement, colors wheel and effects wheel	250	- 255	98%	- 100%
21	lamp power control in conjunction with channel 22	proportional	lamp power adjustment from minimum to maximum (800W - 1400W) when channel 22 is between 171 - 195 dmx	0	- 255	0%	- 100%
22	lamp on/off and motors reset	step	park, no function	0	- 9	0%	- 4%
			lamp off	10	- 29	4%	- 11%
			pan and tilt reset (once only)	30	- 65	12%	- 25%
			all motor reset except dimmer, pan and tilt (once only)	66	- 100	26%	- 39%
			all motor reset except dimmer (once only)	101	- 135	40%	- 53%
			reset of all the motors (once only)	136	- 170	53%	- 67%
			lamp on, enabled power adjustment from 800W to 1400W	171	- 195	67%	- 76%
			lamp on, maximum power	171	- 255	67%	- 100%
Note 1: the display panel may be used to disable the switching off of the lamp via DMX							
Note 2: turning off the lamp and all reset functions are delayed by 6 seconds to prevent accidental activation							
Note 3: the lamp on/off function can only be effected if an opposite level is set							
Projector: coemar infinity Wash		Table name: DMX 512 functions					
Table number: 260		Edition: 2		Date: 23/01/2007			