

DMX controller operation

When the Magnum 1500 is powered on, the LED on the DMX module next to the DIP-switches lights to indicate that a valid DMX signal is being received, and the machine starts to warm up. The Magnum 1500 is ready for operation after approximately 10 minutes.

Set the level on the Magnum 1500's DMX control channel to zero to cut fog output to zero. Increase the level on the machine's DMX control channel to increase the level of fog output.

DMX control channel levels

Level	Percentage	Effect
0-27	0-10%	No fog output
28-255	11-100%	Fog output increases in 24 increments